

Technical Data	GW3048-EM	GW3648-EM	GW5048-EM
<b>Battery Input Data</b>			
Battery Type	Li-Ion or Lead-acid*1	Li-Ion or Lead-acid*1	Li-Ion or Lead-acid*1
Nominal Battery Voltage (V)	48	48	48
Max. Charging Voltage (V)	≤60 (Configurable)	≤60 (Configurable)	≤60 (Configurable)
Max. Charging Current (A)*1	50	50	50
Max. Discharging Current (A)*1	50	50	50
Battery Capacity (Ah)*2	50~2000	50~2000	50~2000
Charging Strategy for Li-Ion Battery	Self-adaption to BMS	Self-adaption to BMS	Self-adaption to BMS
<b>PV String Input Data</b>			
Max. DC Input Power (W)	3900	4600	6500
Max. DC Input Voltage (V)*3	550	550	550
MPPT Range (V)	100~500	100~500	100~500
Start-up Voltage (V)*4	150	150	150
MPPT Range for Full Load (V)	280~500	170~500	230~500
Nominal DC Input Voltage (V)	360	360	360
Max. Input Current (A)	11	11/11	11/11
Max. Short Current (A)	13.8	13.8/13.8	13.8/13.8
No. of MPP Trackers	1	2	2
No. of Strings per MPP Tracker	1	1	1
<b>AC Output Data (On-grid)</b>			
Nominal Power Output to Utility Grid (W)	3000	3680	5000*5
Max. Apparent Power Output to Utility Grid (VA)*6	3000	3680	5000
Max. Apparent Power from Utility Grid(VA)	5300	5300	5300
Nominal Output Voltage (V)	230	230	230
Nominal Output Frequency (Hz)	50/60	50/60	50/60
Max. AC Current Output to Utility Grid (A)	13.6	16	22.8*7
Max. AC Current From Utility Grid (A)	23.6	23.6	23.6
Output Power Factor	~1(Adjustable from 0.8 leading to 0.8 lagging)		
Output THDi (@Nominal Output)	<3%	<3%	<3%
<b>AC Output Data (Back-up)</b>			
Max. Output Apparent Power (VA)	2300	2300	2300
Peak Output Apparent Power (VA)**8	3500,10sec	3500,10sec	3500,10sec
Automatic Switch Time (ms)	10	10	10
Nominal Output Voltage (V)	230 (±2%)	230 (±2%)	230 (±2%)
Nominal Output Frequency (Hz)	50/60 (±0.2%)	50/60 (±0.2%)	50/60 (±0.2%)
Max. Output Current (A)	10	10	10
Output THDv (@Linear Load)	<3%	<3%	<3%
<b>Efficiency</b>			
Max. Efficiency	97.6%	97.6%	97.6%
Max. Battery to Load Efficiency	94.5%	94.5%	94.5%
Euro Efficiency	97.0%	97.0%	97.0%
<b>Protection</b>			
Anti-islanding Protection	Integrated	Integrated	Integrated
PV String Input Reverse Polarity Protection	Integrated	Integrated	Integrated
Insulation Resistor Detection	Integrated	Integrated	Integrated
Residual Current Monitoring Unit	Integrated	Integrated	Integrated
Output Over Current Protection	Integrated	Integrated	Integrated
Output Short Protection	Integrated	Integrated	Integrated
Output Over Voltage Protection	Integrated	Integrated	Integrated
<b>General Data</b>			
Operating Temperature Range (°C)	-25~60	-25~60	-25~60
Relative Humidity	0~95%	0~95%	0~95%
Operating Altitude (m)	≤4000	≤4000	≤4000
Cooling	Natural Convection	Natural Convection	Natural Convection
Noise (dB)	<25	<25	<25
User Interface	LED & APP	LED & APP	LED & APP
Communication with BMS*9	RS485; CAN	RS485; CAN	RS485; CAN
Communication with Meter	RS485	RS485	RS485
Communication with Portal	Wi-Fi	Wi-Fi	Wi-Fi
Weight (kg)	16	17	17
Size (Width*Height*Depth mm)	347*432*175	347*432*175	347*432*175
Mounting	Wall Bracket	Wall Bracket	Wall Bracket
Protection Degree	IP65	IP65	IP65
Standby Self Consumption (W)	<13	<13	<13
Topology	High Frequency Isolation	High Frequency Isolation	High Frequency Isolation
<b>Certifications &amp; Standards</b>			
Grid Regulation	AS/NZS 4777.2:2015, G83/2, G100, CEI 0-21, VDE4105-AR-N, VDE0126-1-1, NRS 097-2-1, RD1699, UNE206006, EN50438		
Safety Regulation	IEC/EN62109-1&2, IEC62040-1		
EMC	EN61000-6-1, EN61000-6-2, EN61000-6-3, EN61000-6-4, EN 61000-4-16, EN 61000-4-18, EN 61000-4-29		

\*1: Lead-acid battery use refers to Approved Battery Options Statement.

The actual charge and discharge current also depends on the battery.

\*2: Under off-grid mode, then battery capacity should be more than 100Ah.

\*3: Maximum operating dc voltage is 530V.

\*4: When there is no battery connected, inverter starts feeding in only if string voltage is higher than 200V.

\*5: 4600 for VDE0126-1-1&VDE-AR-N4105 & CEI 0-21(GW5048-EM).

\*6: For CEI 0-21 GW3048-EM is 3300, GW3648-EM is 4050, GW5048-EM is 5100; for VDE-AR-N4105 GW5048-EM is 4600.

\*7: 21.7A for AS4777.2.

\*8: Can be reached only if PV and battery power is enough.

\*9: The standard configuration is CAN.